

Polycom® Converged Management Application™ (CMA®) Desktop for Mac OS X, Version 5.2.6 Release Notes



Polycom is pleased to announce the release of Polycom® Converged Management Application (CMA) Desktop for Mac OS X, Version 5.2.6. This document provides the latest information about the Polycom CMA Desktop for Mac OS X system and version 5.2.6 software.

For more information about using the features described in this document, refer to the product documentation available at www.polycom.com/videodocumentation.

Software Version History

Version	Release Date	Features
5.2.6	July 2014	Fixes for several issues. Refer to Corrected Issues in Version 5.2.6 for details. Fix for an OpenSSL security vulnerability (CVE-2014-0224).
5.2.5	April 2013	Fixes for several issues.
5.2.4	January 2013	Fixes for several issues.
5.2.3	June 2012	Fixes for several issues.
5.2.2	December 2011	User Interface, online help, and user documentation are available in Simplified Chinese, Traditional Chinese, English, French, German, Japanese, Korean, Russian, and Spanish.
5.2.0	October 2011	Support for placing SIP calls, support for 720p encoding, support for AES Encryption for H.323 calls, support for H.460 for firewall traversal, support for audio and video packet loss recovery, ability to import and export configuration and user profiles, inclusion of call history with Contact details, support for provisioned custom logo, support for dual monitors, ability to install and update from CMA server, support for alphabetically sorted groups.
5.1.1	June 2011	Correction for a defect that prevents CMA Desktop from signing in or registering with a Polycom CMA system running version 5.4.
5.1.0	November 2010	Content sharing using standards-based H.239 protocol, XMPP-based chat, enhancements to viewing and sharing presence, automatic sign-in using network credentials, support for 720p decode, support for H.261, H.263, and H.263+ compression, audio enhancements including 20kHz audio with G.719, 14 kHz Polycom Siren 14, 7 kHz G.722 and G.722.1

Installing and Using Polycom CMA Desktop for Mac OS X, Version 5.2.6



This installation requires the installation of Adobe AIR version 2.0 or above. When prompted to install Adobe AIR, follow the instructions on the screen and then continue the installation of Polycom CMA Desktop for Mac OS X.

Your local administrator will provide the information you need to download the Polycom CMA Desktop for Mac OS X software.

Polycom CMA Desktop for Mac OS X is installed on the partition that includes Mac OS X.



When you upgrade Polycom CMA Desktop for Mac OS X from a previous version to version 5.2.6, you can choose to retain your settings and Contacts list during upgrading.



If your Mac OS X is 10.7.x or above, and your default setting is set as **Allow applications downloaded from Mac App Store and identified developers**, you will get the error message “**CMAD_Mac_Installer.pkg**” can't be opened because it is from an unidentified developer. Your security preferences allow installation of only apps from the Mac App Store and identified developers. Following the instructions below to carry out installation:

- Right click the application icon from **Finder**.
- Select **Open** from the top of contextual menu that appears.
- When prompted, click **Open**, enter the administrator name and password if required.

- 1 To download the .dmg file for Polycom CMA Desktop for Mac OS X version 5.2.6:
- 2 On your Mac, open Safari.
- 3 Go to support.polycom.com.
- 4 Select **Documents and Downloads > Telepresence and Video**.
- 5 Select **Polycom Converged Management Application CMA Desktop**.
- 6 Download the .dmg file for Polycom CMA Desktop for Mac OS X version 5.2.6.

To install Polycom CMA Desktop for Mac OS X version 5.2.6:

- >> Double-click the .dmg file for Polycom CMA Desktop for Mac OS X version 5.2.6 to start the installation, and follow the prompts on the screen.

To upgrade Polycom CMA Desktop for Mac OS X from a previous version:

- 1 Make a note of your current Polycom CMA Desktop for Mac OS X settings and information about your contacts.
- 2 Double-click the .dmg file for Polycom CMA Desktop for Mac OS X version 5.2.6 to start the installation, and follow the prompts on the screen.

To uninstall Polycom CMA Desktop for Mac OS X version 5.2.6:

- >> Go to **Applications/Polycom CMA Desktop**, and double-click **Uninstall Polycom CMA Desktop**.

For more information about using Polycom CMA Desktop for Mac OS X, click the application menu and choose **Help**.

Starting Polycom CMA Desktop for Mac OS X

You can use your credentials to sign in to only one instance of Polycom CMA Desktop for Windows or Polycom CMA Desktop for Mac OS X. If you are signed in on one system, be sure to sign out before you attempt to sign on to another system.



If you use a VPN, you must connect to the VPN before starting Polycom CMA Desktop.

To start Polycom CMA Desktop for Mac OS X:

- >> Go to **Applications > Polycom CMA Desktop**, and double-click Polycom CMA Desktop.




To make sure you are always ready to send or receive calls, do the following:

- Go to **Polycom CMA Desktop > Preferences > Sign In**, and configure the application to start and sign you in when the system starts.
- Go to **Applications > Polycom CMA Desktop**, and drag the Polycom CMA Desktop for Mac OS X icon to the dock.

Getting Started with Polycom CMA Desktop for Mac OS X

Polycom CMA Desktop is simple and intuitive to use. To get started, here are some things you can try.

- Add people to your Contacts list.
1. Click the Directory ()

2. Start typing a name. The system shows you all entries that contain the characters you enter as you type.

For example, if you type *and*, your search may find entries such as *Andrew Jones*, *Christine Anderson*, or *Andover Conference Room*.



3. If your system is configured for manual searching, click the Search button to start the search.

Tip: For faster searches in large Directories, click ▼ and choose the Group that contains the person you're looking for, if you know it.

4. Click the name of the person you want to add.

5. Click **Add to Contacts**.

— Call someone. Try either of the following:

- » Click a name in your Contacts list or your Recent Calls, and then click  **Call**.
- » Type a name or number, and then click  **Call**.



The Directory includes current Polycom CMA Desktop users whom you can call, as well as people whose accounts are not yet active. A Polycom CMA Desktop account is activated when the person signs in for the first time. If you want to call a person whose account is not activated, tell him or her to activate the account by signing in. You can then locate the user in the Directory and place a call.

New Features in Version 5.2.3

The version 5.2.3 software includes the features and functionality of version 5.2.2, along with enhancements to address several problems.

New Features in Version 5.2.2

Version 5.2.2 includes the following enhancements:

- User Interface, online help and user documentation are available in Simplified Chinese, Traditional Chinese, English, French, German, Japanese, Korean, Russian, and Spanish.

New Features in Version 5.2.0

Version 5.2.0 includes the following enhancements:

- Support for placing SIP calls

- Ability to 720p encode
- Ability to zoom in on content
- Support for AES Encryption for H.323 call
- Support for H.460 for firewall traversal
- Support for audio and video packet loss recovery
- Ability to import and export configuration and user profile
- Call history included with Contact details
- Support for provisioned custom logo
- Support for notification Log
- Support for dual monitors
- Ability to install and update from CMA server
- Support for network quality of service
- Additional options for provisioned settings
- Support for alphabetically sorted groups

New Features in Version 5.1.1

Polycom CMA Desktop for Mac OS X version 5.1.0 had a defect that prevents it from signing in or registering with a Polycom CMA system running version 5.4. This issue has been corrected on Polycom CMA Desktop for Mac OS X version 5.1.1.

New Features in Version 5.1.0

Version 5.1.0 includes the following enhancements:

- Content sharing using standards-based H.239 protocol
- XMPP-based chat
- Ability to view presence for Contacts
- Ability to show others your presence
- Automatic sign-in using network credentials
- Support for 720p decode (720p encode is not supported)
- Support for H.261, H.263, and H.263+ compression
- Audio enhancements including 20kHz audio with G.719, 14 kHz Polycom Siren 14, 7 kHz G.722 and G.722.1

Platform-Specific Limitations

Support for the following features are not included in this software version:

- Contact cards
- Starting a call automatically by clicking a callto: link
- Directory search results limited to people and systems that can support calls
- Directory status on the CMA server
- Integration with eBeam Workspace

Corrected Issues in Version 5.2.6

The following table lists corrected issues in version 5.2.6.

Feature	Issue ID	Description
Installation	VIDESC-12094	CMA Desktop cannot be installed on Mac with Adobe AIR 13.
Interoperability	CMAD-10548	CMA Desktop users occasionally fail to register to the gatekeeper through VBP® ST due to incorrect Endpoint ID.
Interoperability	VIDESC-11774	CMA Desktop cannot playback recordings using Quick Code.
Interoperability	VIDESC-11737	CMA Desktop users are not able to launch the application since they are quarentined on DMA server.
User Interface	VIDESC-11762	CMA Desktop does not delete missed calls from the main window after the call log has been deleted.

Corrected Issues in Version 5.2.5

The following table lists corrected issues in version 5.2.5.

Feature	Issue ID	Description
User Interface	CMAD-10483	Newly created CMA Desktop contacts group could not display if the preferences flag Show Recent Calls in Contact List was not ticked. This issue has been fixed.
Signing In	CMAD-10523	When using NTLM v2 authentication, manual method of logging into Resource Manager did not work on the CMA Desktop client. This issue has been fixed.
Installation	CMAD-10521	A security issue allowing a potential privilege escalation by a user has been addressed. Polycom recommends all customers upgrade to this version. This issue has been fixed.

Corrected Issues in Version 5.2.4

The following table lists corrected issues in version 5.2.4.

Feature	Issue ID	Description
Call Control	CMAD-10499	The application crashes sometimes with this error prompt <i>internal error occurred</i> .
Call Control	CMAD-10328	Sometimes, after you reject an incoming call, the incoming call window freezes and cannot be closed.
Call Control	CMAD-8148	If a Polycom HDX systems from an ISDN network joins the call through a Polycom RMX gateway, and your CMA Desktop application is of the version 5.2.2, you cannot receive content sent from this Polycom HDX system.
Directory	CMAD-9065	If your Polycom CMA Desktop application is of the version 5.2.2, and you log in as an Active Directory user, you cannot see other Active Directory users in the same group.
General	CMAD-10482	If you copy and sent a large amount of the chat messages, the Chat window will be closed, and you may be logged out and in repetitively.
General	CMAD-10424	When you add contacts from search results, the contact's detail information is not copied into your CMA Desktop application.
General	CMAD-9019	Timestamps included in Call Detail Report (CDR) sent from the Polycom CMA Desktop version 5.2.2 to the Polycom CMA system are incorrect.
General	CMAD-10329	Duplicate contact entries exist in CMA Desktop application version 5.2.3.
General	CMAD-10130	After you upgrade your Polycom CMA Desktop from version 5.2.2 to 5.2.3, you cannot receive video from the Logitech QuickCam Messenger.

Feature	Issue ID	Description
Interoperability: RMX1500	CMAD-10442	When a Polycom CMA Desktop application of the version 5.2.2 or 5.2.3 connects to a Polycom RMX meeting room, you cannot receive people video till 10 seconds later.
Provisioning and Call Control	CMAD-10129	When you log in to the Polycom CMA Desktop application, the default calling type is always set as H.323, even when H.323 calling is disabled in Site Provisioning in the Polycom RealPresence Resource Manager.
User Interface	CMAD-10327	When you are using dual-monitor, if you drag to move the Polycom CMA Desktop window to the second monitor, the video window cannot be moved.
User Interface	CMAD-10326	You cannot close the chat window using the key combination "cmd-w" as expected.
Video	CMAD-9799	When you are in a call with a Polycom HDX system, and your far end selects different camera source, your local Picture-in-Picture (PIP) disappears.

Corrected Issues in Version 5.2.3

The following table lists corrected issues in version 5.2.3.

Feature	Issue ID	Description
Calling	CMAD-7751	In the previous version, when you added a contact from the Recent Calls list, the system did not correctly add Annex O dialing information (alias@domain.com). This problem has been fixed.
General	CMAD-7748	Previously, when you upgraded from version 5.1 to the 5.2.2 software version, the 720p people video transmit frame rate decreased from a maximum of 25fps to a maximum of 10fps. This problem has been resolved.
Interoperability: Codian MCU	CMAD-7745	When the Polycom CMA Desktop system called into a Codian MCU using a Codian IP gateway, CMA Desktop connected as audio only. This problem has been fixed.
User Interface	CMAD-7746	In the previous version, some user interface text was missing when you install Polycom CMA Desktop on an operating system other than English, German, Korean, French, Simplified Chinese, Traditional Chinese, Japanese, Russian, or Spanish. For example, this problem occurred on systems running the Portuguese operating system. This problem has been resolved.

Corrected Issues in Version 5.2.2

The following table lists the corrected issues in version 5.2.2.

Feature	Jira ID	Description
Interoperability	CMAD-4603	Codian MCU 4505 did not recognize DTMF tones from Polycom CMA Desktop in SIP calls. This issue has been fixed.
Call Control	CMAD-4542	You could not place an H.323 call between Polycom CMA Desktop and ViewStation. This issue has been fixed.
Video	CMAD-4541	Polycom CMA Desktop did not transmit video to FX system in a H.323 call. This issue has been corrected.
Installation	CMAD-5273	If the CMA server sends a message that an upgrade for Windows systems from previous version to 5.2.2 or later versions is required, the CMA Desktop for Mac OS X system displayed the upgrade message which is incompatible for Mac. This problem has been corrected.

Corrected Issues in Version 5.2.0

The following table lists corrected issues in version 5.2.0.

Feature	Issue ID	Description
Signing In	CMAD-1888 VIDESC-7144	Polycom CMA Desktop version 5.1 could not register with a gatekeeper. This issue has been corrected on version 5.2.
Signing In	CMAD-2188 VIDESC-7236	Polycom CMA Desktop version 5.1 could not register with a Polycom CMA system running version 5.4. This issue has been fixed on Polycom CMA Desktop version 5.2.
Signing In	CMAD-2402 CMAD-2425	Polycom CMA Desktop version 5.1 could not login if 64-bit preferred order was set to the top. This issue has been corrected on version 5.2.
Directory	CMAD-2803 VIDESC-7032	Previously, the directory search resulted all the LDAP contacts including the offline ones and the ones with no device registered. This issue has been corrected.
Interoperability	CMAD-2770 VIDEO-82580	Previously, if Polycom CMA Desktop made a call to a third party endpoint, CMA Desktop got green screen or pink screen. This issue has been corrected.
Video	CMAD-232	Previously, there was no video when a Microsoft HD Camera was connected to Polycom CMA Desktop version 5.1. This issue has been corrected on version 5.2.
Content	CMAD-1399	When CMA Desktop connected at 128 kbps or 256 kbps to a conference hosted by RMX 2000, the H.263 content quality on CMA Desktop was bad. This issue has been corrected.
Content	CMAD-2956	Previously, CMA Desktop could not zoom in on content on the secondary monitor. This issue has been corrected.
CMA Management	CMAD-1115	A problem has been resolved that prevented the CMA Desktop for Mac OS X system running version 5.1.0 from signing in to CMA server running version 5.4.
CMA Provisioning	CMAD-2698	A problem has been resolved that caused the system to ignore the new value when the Maximum Time in Call provisioned new changed.
Instant Message	CMAD-1471	Previously, if you input a link containing uppercase letter in the instant message, it was not recognized as a link. This issue has been corrected.
Interoperability: RMX 2000	CMAD-1390	A problem has been resolved that prevented the system from hanging up a call with RMX 2000.

Feature	Issue ID	Description
Stability	CMAD-715	In previous versions, after thousands of calls, the Java processor of Polycom CMA Desktop crashed when you attempted to place a new call. This issue has been corrected.
Stability	CMAD-75	In previous versions, after several calls, the media processor of Polycom CMA Desktop might crash. This issue has been corrected.
Video	CMAD-3280	Previously, there was no video when CMA Desktop retrieved an on-hold Broadsoft SIP call. This issue has been corrected.

Feature Limitations

The following table lists the known feature limitations for this software version. If a workaround is available, it is noted in the table.

Feature	Issue ID	Found in Release	Description	Workaround
Call Control	CMAD-3359	5.2.0	When RMX 4000 invites CMA Desktop into a SIP call, the call keeps ringing after CMA Desktop answered.	Let RMX place an H.323 call when it invites CMA Desktop to the conference.
Call Control	CMAD-3353	5.2.0	When HDX places a SIP call to CMA Desktop at a call rate higher than 1024 kbps, CMA Desktop cannot send or receive content.	None
Call Control	CMAD-3345	5.2.0	After the call is connected, if the direct mode gatekeeper on Polycom CMA server is disabled, the call would disconnect.	None
Call Control	CMAD-4508	5.2.0	If Polycom CMA Desktop registers with a Polycom CMA server as a backup gatekeeper, you cannot place a call on CMA Desktop by inputting E.164 or H.323 alias.	Input the IP address to make a call.
Call Control	CMAD-4517	5.2.0	The call disconnects if the direct mode of Polycom DMA Gatekeeper is down.	Register with a Gatekeeper and place the call again.
Call Control	CMAD-4543	5.2.0	Memory leak occurs after hundreds of calls on Polycom CMA Desktop.	Close Polycom CMA Desktop and start it again.

Feature	Issue ID	Found in Release	Description	Workaround
Call Control	CMAD-4545	5.2.0	If you place a call by dialing an Avaya Call Manager number managed by Polycom DMA version 4.0, the call is audio-only.	None
Call Control	CMAD-4542	5.2.0	You cannot place a H.323 call between Polycom CMA Desktop and ViewStation.	None
Calling	CMAD-8232	5.2.2	If the CMA Desktop system is registered to a provisioning server that has H.323 and SIP calling disabled, placing a call causes the CMA Desktop system to crash.	Register to a provisioning server that has H.323 or SIP calling enabled, and try the call again.
Calling	CMAD-7957	5.2.0	Annex O (alias@domain.com) addresses that were added to the Recent Calls list or Call Log in a previous software version cannot be added to the Contacts list correctly in this software version.	Manually dial the Annex O address, and then add the Contact from your Recent Calls list.
Calling	DOC-250	5.1	When you use the Directory to place call to a Polycom OTX telepresence room, you are prompted to choose which of the HDX systems associated with the telepresence room to call. If you choose a system other than the first system, the call has no audio.	Try the call again, and choose the first system associated with the telepresence room.
CMA Management	CMAD-4186	5.2.0	The CMA Desktop system displays an error message that the user name and password are incorrect if the account is disabled or locked.	Go to CMA server and enable or unlock the account.
Content	CMAD-8166	5.2.2	When you run the CMA Desktop system on Mac OS 10.6 and show a PowerPoint (.pptx) presentation as content, the far end sees the content as green video.	Upgrade the Mac OS to version 10.7.
Content	CMAD-4191	5.2.0	Content is disabled if CMA Desktop dials in a conference on RMX 4000 through SIP call.	None

Feature	Issue ID	Found in Release	Description	Workaround
Content	CMAD-4527	5.2.0	In a SIP conference with Polycom RMX 1000, Polycom CMA Desktop receives content from the video channel.	None
Content	CMAD-4528	5.2.0	In a SIP call from Lync registered Polycom HDX system to Polycom CMA Desktop, CMA Desktop cannot send content.	None
Content	CMAD-3353	5.2.0	When HDX places a SIP call to CMA Desktop at a call rate higher than 1024 kbps, CMA Desktop cannot send or receive content.	None
Directory	CMAD-4514	5.2.0	If Active Directory is used as a LDAP server, when Polycom CMA Desktop imports a contact from the LDAP server, the IP field might be filled with other information, such as E.164.	None
Gatekeeper	CMAD-7734	5.2.3	The Polycom CMA Desktop system does not show a notification if gatekeeper registration fails due to an invalid gatekeeper hostname.	None
General	CMAD-6081	5.2.0	You may experience crashes when you run CMA Desktop on iOS 10.7.2.	Follow these steps: On your Mac, go to System Preferences > Energy Saver. Disable Automatic Graphics Switching.
General	CMAD-8247	5.2.3	Occasionally, entries are duplicated in the Contacts list.	Delete one of the duplicates to remove all duplicates of an entry.
Installation	CMAD-3613	5.2.0	On rare occasions, you get a message saying "An error occurred while installing Adobe Air. Installation may not be allowed by your administrator. Please contact your admin." when start the CMA Desktop after installation.	Reinstall Adobe Air, then restart the CMA Desktop.

Feature	Issue ID	Found in Release	Description	Workaround
Interoperability	CMAD-7872	5.2.3	When signing in to the CMA server through the Polycom VBP system, Polycom CMA Desktop is unable to display the message prompting users to upgrade.	Wait for the Polycom CMA Desktop system to poll the CMA server for the required software version. By default, the CMA system's Software Update Polling Interval is set to 60 minutes.
Interoperability	CMAD-7741	5.2.0	In a H.323 call with a Tandberg C20 system, the Polycom CMA Desktop system is unable to control the far-end camera.	None
Interoperability	CMAD-7742	5.2.3	In a SIP call hosted by a Polycom HDX9006 system, Polycom CMA Desktop sometimes is unable to display content.	None
Interoperability	CMAD-8237	5.2.3	In a SIP call originated by a Polycom HDX system running software version 3.0.5, the CMA Desktop system is sometimes unable to send or receive content.	Originate the call from the CMA Desktop system.
Interoperability	CMAD-4415	5.2.0	In a call with Polycom MGC at 1920 kbps, if the video is defined as H.261 or H.263, CMA Desktop will be negotiated as secondary.	None
Interoperability	CMAD-4529	5.2.0	You cannot place a call to Tandberg 6000e at 1920 kbps. If you receive a call from Tandberg 6000 at 1920 kbps, the call is not encrypted.	None
Interoperability	CMAD-4546	5.2.0	There is no video nor audio in a Point-to-Point call between Polycom CMA Desktop and Avaya OneXC. CMA Desktop is in a held state.	None
Interoperability	CMAD-4515	5.2.0	When Polycom CMA Desktop is in a SIP call with Sony PCS-XG80, the Far End Camera Control function doesn't work.	Place an H.323 call.

Feature	Issue ID	Found in Release	Description	Workaround
Interoperability	CMAD-4603	5.2.0	Codian MCU 4505 does not recognize DTMF tones from Polycom CMA Desktop in SIP calls.	None
Interoperability	CMAD-10497	5.2.4	You cannot receive content in SIP calls hosted through a Polycom RMX version 7.8 system.	If you are the first one to send content in the meeting, you can receive content shared by others later.
LDAP	CMAD-3493	5.2.0	It takes a long time to return the results if there are many when you search from Directory.	None
Network	CMAD-8123	5.2.0	When a RealPresence Mobile system places a SIP call to the CMAD Desktop system through the ACME session border controller, the Desktop system sees the incoming call notice, but the call cannot be established.	Place the call from the CMA Desktop system.
Network	CMAD-8265	5.2.2	When a CMA Desktop system running software version 5.2.2 accesses the network using a VBP, it is unable to sign in to the Polycom XMA system.	Upgrade to software version 5.2.3, available at support.polycom.com .
Signing In and Out	CMAD-8156	5.2.2	If you sign in to the CMA Desktop system using the Polycom DMA system as gatekeeper and then sign in to the same account from a different IP address, you see a message that gatekeeper registration failed.	Wait 6 minutes, and then try signing in again.
Signing In and Out	CMAD-2808	5.2.0	Occasionally, your CMA Desktop domain account (Preferences > Sign In, network login credentials) displays wrong if you select "launch CMA Desktop now" after installation.	Do not select "launch CMA Desktop now" after installation. Exit and sign in to CMA Desktop again.
Signing In and Out	CMAD-3340	5.2.0	Sometimes, you cannot start CMA Desktop when a warning message shows reinstall the Adobe Air Runtime.	Start CMA Desktop again.
User Interface	CMAD-265	5.2.0	You cannot search a Group in the directory.	None

Feature	Issue ID	Found in Release	Description	Workaround
User Interface	CMAD-4068	5.2.0	It always opens the help page in Safari browser.	None
User Interface	CMAD-4067	5.2.0	It always opens a new help window when you press COMMAND +SHIFT+H or click Help menu.	None
User Interface	CMAD-3889	5.2.0	If Google web browser is set to the default browser, the help cannot be displayed.	Use other web browser as the default browser.
User Interface	CMAD-4516	5.2.0	In a SIP call between a Polycom CMA Desktop and a Polycom HDX system running version 3.0.1, the mute status of the HDX system cannot be shown on the call window of CMA Desktop.	None
User Interface	CMAD-2406	5.2.0	The mute status of HDX does not show on the call window of CMA Desktop during a SIP call.	None
Video	CMAD-4525	5.2.0	In a H.323 call with High Profile enabled Polycom RSS 4000 system, Polycom CMA Desktop gets frozen video after using the Far End Camera Control function.	None
Video	CMAD-4541	5.2.0	Polycom CMA Desktop does not transmit video to the FX system in a H.323 call.	None

Hardware and Software Requirements

These hardware and software requirements have been determined based on test scenarios. Your system's actual performance may vary based on software or hardware configurations.

Operating System	Mac OS X 10.8 Mountain Lion Mac OS X 10.7 Lion Mac OS X 10.6 Snow Leopard
Macintosh Models	Systems with x86 processor (with the exception of MacBook Air) Note: You might be able to run Polycom CMA Desktop on MacBook Air if the CPU load is low and the ambient temperature is cool.
Processor	<p>Polycom CMA Desktop for Mac OS X system's capabilities vary depending on processor performance. The processor types and speeds listed below are intended as reference guides. Polycom CMA Desktop for Mac OS X has equivalent capabilities on other processors with equivalent performance.</p> <p>Basic video (Up to QVGA): Intel Core2 Duo 2 CPUs 1.6 GHz Premium (up to VGA, People + Content):</p> <ul style="list-style-type: none"> • Intel Core 2 Duo 2.0 GHz, • Intel Core i3 2 CPUs 1.6 GHz • Intel Core i5 2 CPUs 1.6 GHz or higher <p>HD Transmit (Up to 720p):</p> <ul style="list-style-type: none"> • Core i3 4 CPUs 1.8 GHz or higher (up to 15 fps) • Core i3 2 CPUs 2.5 GHz or higher (up to 15 fps) • Core i5 4 CPUs 2.0 GHz or higher (up to 30 fps) <p>HD Receive (up to 720p):</p> <ul style="list-style-type: none"> • Core2 Duo 2 CPUs 1.6 GHz or higher (up to 15fps) • Core 2 Duo CPU 2.0 GHz or higher (up to 30fps) • Core i5 4 CPUs 2.0 GHz or higher (up to 30fps) <p>Note: Actual performance may vary based on software or hardware configurations. The processor types and speeds listed are for reference only. Polycom CMA Desktop will have equivalent capabilities on other processors with equivalent performance.</p>
RAM	2 GB
Video Memory	256 MB Vidwo RAM
Hard Drive Space	200 MB

Cameras	<p>USB 2.0 Web Cameras:</p> <ul style="list-style-type: none"> • iSight built-in camera on Mac • Microsoft LifeCam Studio • Microsoft LifeCam Cinema • Microsoft LifeCam HD-5000 • Microsoft LifeCam HD-6000 • Microsoft LifeCam HD-7000 • Logitech QuickCam Vision Pro for Mac • Logitech Webcam Pro 9000 • Logitech Webcam C100, C160, C210, C270, C310, C600, and C905. <p>Note: Polycom has fully qualified the USB devices listed above for interoperation with Polycom CMA Desktop for Mac OS X. Other Macintosh USB devices may also work with Polycom CMA Desktop for Mac OS X.</p>
Audio Devices	<ul style="list-style-type: none"> • Built-in microphone on MacBook, MacBook Air, MacBook Pro, iMac, and Apple LED Cinema Display • Built-in microphone on Logitech QuickCam Vision Pro • Built-in microphone on Logitech 2MP Webcam C600 • Logitech ClearChat Comfort • Logitech PC Headset 960 • Somic Headset DT-893 • Philips 3.5mm SHM7110U Headset • Logitech PC Headset 860 • Logitech USB Headset H330, H530
Monitor	XGA, 16-bit color or higher
Network Access	Network 128 kbps and above (Cable, DSL, or LAN)
VPN Client	<p>The VPN client must meet these requirements:</p> <ul style="list-style-type: none"> • Must appear in the Mac system's network adapter list. • Must allow Polycom CMA Desktop for Mac OS X to retrieve the VPN client's IP address from the adapter. • Must not block any ports required by Polycom CMA Desktop. For a list of ports, see Inbound and Outbound Ports, later in this document. <p>These requirements are met by most VPN clients, such as Juniper Network Connect client, version 6.5.0.</p>
Polycom CMA System	5.4.0, 5.5.0 ER19, 6.0.0

Interoperability

The following list indicates the products that have been tested for compatibility with this release:

Type	Product	Version
NAT/Firewall/Border Controller	Polycom VBP™ 5300-ST	11.2.11
Management Systems and Recorders	Polycom CMA 4000, CMA 5000	6.0.1
	Polycom DMA™ 7000	4.0.3 / 5.0
	Polycom RSS™ 4000	8.0
Gatekeeper, Gateways, External MCU, Bridges, Call Managers	Polycom PathNavigator	7.1.10.001
	Polycom ReadManager® SE200	3.00.07.ER001
	Polycom RMX 2000™	7.6.0 / 7.7
	Polycom MGC™	9.0.1.6
Endpoints	LifeSize Room	4.7.10
	Polycom Telepresence m100	1.0/1.0.4/1.0.5
	Polycom CMA Desktop	5.1 / 5.2.2 / 5.2.3/5.2.4/5.2.5
	Polycom CMA Desktop for Mac OS X	5.1 / 5.2.2 / 5.2.3/5.2.4/5.2.5
	Polycom HDX®	3.0.4 / 3.0.5
	Polycom PVX®	8.0.16
	Polycom RealPresence® Mobile	1.2 / 1.3
	Polycom QDX™ 6000	4.0.2
	Polycom VSX® 7000, VSX 7000A, VSX 8000	9.0.6.2
	Polycom VVX	4.0.2B
	LifeSize Room	4.7.10
	TANDBERG C20	TC3.1.1

Supported Protocols, Algorithms, and Ports

Protocols

This version of Polycom CMA Desktop for Mac OS X supports the following protocols:

Protocol	Description
DNS	Domain Name System
H.235	Security and Encryption
H.239	Token Management
H.281	Far End Camera Control (FECC)
H.323	Call signaling and control, multimedia transport and control, bandwidth control
H.460.18 H.460.19	Firewall/NAT traversal
LDAP, H.350	Directory Services
NTLMv1, NTLMv2	Authentication
Polycom LPR™	Lost Packet Recovery
SIP	Session Initiation Protocol
XMPP	Presence, instant messaging

Video Resolutions

This version of Polycom CMA Desktop for Mac OS X supports the following resolutions for People video:

Call Speed	Video Format	Resolution
64 kbps - 511 kbps	QVGA	320x240
512 kbps - 1023 kbps	VGA	640x480
1024 kbps - 1920 kbps	720p	1280x720



Actual transmitted video resolution is determined by several factors, such as camera capability, computer performance, network conditions, the far-end system's capabilities, and whether content is being sent or received.

Algorithms

This version of Polycom CMA Desktop for Mac OS X supports the following algorithms:

Algorithm Type	Description
Audio	G.719 (mono) Constant Bit Rate (CBR) at 32 kbps, 48 kbps, 64 kbps, 96 kbps, and 128 kbps G.722.1 at 16 kbps, 24 kbps and 32 kbps G.722.1 Annex C at 24 kbps, 32 kbps, and 48 kbps G.711u, G.711a, G.722, G.728, and G.729a for VOIP Interoperability Siren 14 at 24 kbps, 32 kbps, and 48 kbps SirenLPR
Video	H.261 H.263 H.263+ H.264
Encryption	AES supported in H.323 calls

Inbound and Outbound Ports

This version of Polycom CMA Desktop for Mac OS X uses the following inbound and outbound ports:

Inbound Ports

Port	Function
1720 (TCP)	H.225.0 CS
1719 (UDP)	H.225.0 RAS
3230 - 3237 (TCP)	H.245
3230 - 3237 (UDP)	Media (RTP/RTCP), configurable on provisioning server
5060 (TCP/UDP)	SIP
Random port (TCP)	BFCP

Outbound Ports

Port	Function
5060 (UDP)	SIP
Random port (TCP)	SIP
Random port (TCP)	BFCP
Random port (UDP)	DNS
Random port (TCP)	HTTPS
Random port (TCP)	LDAP
Random port (TCP)	XMPP
1719 (UDP)	H.225.0 RAS
3230 - 3237 (TCP)	H.225.0 CS
3230 - 3237 (TCP)	H.245
3230 - 3237 (UDP)	Media (RTP/RTCP) - configurable on provisioning server

Improving Video Quality

Factors Affecting Video Quality

A number of factors can affect video quality, including the quality and design of your camera, your camera settings, your video window size, and lighting conditions. If your video preview shows reduced quality in your local video, be sure to address these problems, if possible. Any deficiencies you see locally may be magnified when the video is sent to the far end. Video problems may be more obvious when the video is expanded to fill the full screen.

Troubleshooting Video Problems

Problems with Video Quality

If you are using CMA Desktop on a laptop, ensure that the laptop is connected to a power source. Running on battery power can reduce the laptop's performance, resulting in poor video quality or no video.

Problems with No Video

Check your Macintosh system's firewall configuration. To do this, follow these steps:

- 1 Go to **System Preferences > Security > Firewall > Advanced**.
- 2 Add the Polycom CMA Desktop application to the list.
- 3 Select **Allow incoming connections**.

If local video cannot be seen by far end when connected through juniper VPN, refer to the below comments:

- 1 Go to **Preferences > Network**, and check QoS setting;
- 2 Select **Never use QoS**.

Notes:

There are two options on QoS setting:

- **Never use QoS:** Disable the QoS function on Polycom CMA Desktop.
- **Let provisioning server enable or disable QoS:** Let Polycom CMA Desktop use the QoS value provisioned by Polycom CMA server.

Problems with Video Window Size

If the size of the far-end video seems small, you can resize the far-end video window manually or you can view it full screen. The size of the far-end video window is determined by the resolution or format of the video sent by the far end, so video sent by endpoints that transmit lower resolution video display in a smaller window.

Improving Audio Quality

Factors Affecting Audio Quality

Polycom CMA Desktop uses the built-in Polycom echo canceller which automatically adjusts the audio to prevent the sound of far-end voices from being sent back to the far end.

A number of factors can affect audio quality, including the volume of the system, the sensitivity of the microphone, the acoustic qualities of the room, and the acoustic qualities of any audio devices that combine microphone and speakers.

Troubleshooting Audio Problems

- For best audio echo cancellation performance, all audio signal processing should be disabled. If you are experiencing audio issues, make sure audio processing software provided by your computer manufacturer is disabled.
- Disable ambient noise reduction on the system. To do this:
 1. Go to **System Preferences > Sound > Input**.
 2. Disable **Use ambient noise reduction**.
- If you use a separate microphone, ensure that it is connected to a USB port on your computer and not to a USB hub connected to the computer.
- For best microphone performance, place the microphone at a distance from the person who is speaking. Speaking too closely to the microphone can cause poor audio quality.

Problems with Echo

If the far end hears echo, try these steps:

- Check your audio device's echo cancellation settings.

If your audio device provides its own echo cancellation, be sure to enable it. Refer to the documentation you received with your device.

- Check your volume.

For most effective echo cancellation, reduce the volume on your system's speakers, and then adjust the sound using the Polycom CMA Desktop volume controls.

- Place the microphone and speakers as far apart as possible.

If you use a laptop's integrated speakers with the laptop's integrated microphone or with a webcam's microphone, connect external speakers to allow you to increase the distance between the microphone and speakers.

- If you still experience echo, use earphones instead of speakers. You can also use a headset instead of a microphone and speakers.

Problems with No Audio

Check your Macintosh system's firewall configuration. To do this, follow these steps:

- 1 Go to **System Preferences > Security > Firewall > Advanced**.
- 2 Add the Polycom CMA Desktop application to the list.
- 3 Select **Allow incoming connections**.

Collecting Diagnostic Information

If you need to report a problem, you may be asked to supply information about your system. You can find diagnostic information in these locations:

File	Location
Log	/UserName/Library/Application Support/Polycom CMA Desktop/Log/cmad.log
Crash Reports	/UserName/Library/Logs/DiagnosticReports/Polycom CMA Desktop_timestmap_username-model.crash /UserName/Library/Logs/DiagnosticReports/MediaProcessor_timestmap_username-model.crash
Provisioned Data	/UserName/Library/Application Support/Polycom CMADesktop/configuration.xml

To collect Polycom CMA Desktop Diagnostics:

- 1 From the main window, click the application menu and choose **Preferences > Statistics > Log**.
- 2 Click **Save Log**.
- 3 Specify the file name and location for the zipped file.
- 4 Click **Save**.

To collect the Macintosh system profile on Mac OS X 10.6:

- 1 From the applications folder, click **Utilities > System Profiler**.
- 2 Choose **File > Save As** and specify the location.

To collect the Macintosh system profile on Mac OS X 10.7:

- 1 From the applications folder, click **Utilities > System Information**.
- 2 Choose **File > Save** and specify the location.

Related Documentation

For more information, see the *Release Notes for Polycom Converged Management Application 5000*, available at support.polycom.com.

Get Help

For more information about installing, configuring, and administering Polycom products, refer to Documents and Downloads at [Polycom Support](#).

To find all Polycom partner solutions, see [Polycom Global Strategic Partner Solutions](#).

For more information on solution with this Polycom partner, see the partner site at [Polycom Global Strategic Partner Solutions](#).

The Polycom Community

The [Polycom Community](#) gives you access to the latest developer and support information. Participate in discussion forums to share ideas and solve problems with your colleagues. To register with the Polycom Community, create a Polycom online account. When logged in, you can access Polycom support personnel and participate in developer and support forums to find the latest information on hardware, software, and partner solutions topics.

Copyright© 2014, Polycom, Inc. All rights reserved. No part of this document may be reproduced, translated into another language or format, or transmitted in any form or by any means, electronic or mechanical, for any purpose, without the express written permission of Polycom, Inc.

6001 America Center Drive
San Jose, CA 95002
USA



Polycom®, the Polycom logo and the names and marks associated with Polycom products are trademarks and/or service marks of Polycom, Inc. and are registered and/or common law marks in the United States and various other countries. All other trademarks are property of their respective owners. No portion hereof may be reproduced or transmitted in any form or by any means, for any purpose other than the recipient's personal use, without the express written permission of Polycom.



Java is a registered trademark of Oracle America, Inc., and/or its affiliates.

End User License Agreement By installing, copying, or otherwise using this product, you acknowledge that you have read, understand and agree to be bound by the terms and conditions of the End User License Agreement for this product. The EULA for this product is available on the Polycom Support page for the product.

Patent Information The accompanying product may be protected by one or more U.S. and foreign patents and/or pending patent applications held by Polycom, Inc.

Open Source Software Used in this Product This product may contain open source software. You may receive the open source software from Polycom up to three (3) years after the distribution date of the applicable product or software at a charge not greater than the cost to Polycom of shipping or distributing the software to you.

Disclaimer While Polycom uses reasonable efforts to include accurate and up-to-date information in this document, Polycom makes no warranties or representations as to its accuracy. Polycom assumes no liability or responsibility for any typographical or other errors or omissions in the content of this document.

Limitation of Liability Polycom and/or its respective suppliers make no representations about the suitability of the information contained in this document for any purpose. Information is provided "as is" without warranty of any kind and is subject to change without notice. The entire risk arising out of its use remains with the recipient. In no event shall Polycom and/or its respective suppliers be liable for any direct, consequential, incidental, special, punitive or other damages whatsoever (including

without limitation, damages for loss of business profits, business interruption, or loss of business information), even if Polycom has been advised of the possibility of such damages.

Customer Feedback We are striving to improve our documentation quality and we appreciate your feedback. Email your opinions and comments to DocumentationFeedback@polycom.com.

Polycom Support Visit the [Polycom Support Center](#) for End User License Agreements, software downloads, product documents, product licenses, troubleshooting tips, service requests, and more.