



Getting Started Guide

1.8 | December 2014 | 3725-69809-004/A

Polycom® RealPresence® Capture Server - Virtual Edition



Copyright© 2014, Polycom, Inc. All rights reserved. No part of this document may be reproduced, translated into another language or format, or transmitted in any form or by any means, electronic or mechanical, for any purpose, without the express written permission of Polycom, Inc.

6001 America Center Drive
San Jose, CA 95002
USA

Trademarks Polycom®, the Polycom logo and the names and marks associated with Polycom products are trademarks and/or service marks of Polycom, Inc. and are registered and/or common law marks in the United States and various other countries.



All other trademarks are property of their respective owners. No portion hereof may be reproduced or transmitted in any form or by any means, for any purpose other than the recipient's personal use, without the express written permission of Polycom.

Disclaimer While Polycom uses reasonable efforts to include accurate and up-to-date information in this document, Polycom makes no warranties or representations as to its accuracy. Polycom assumes no liability or responsibility for any typographical or other errors or omissions in the content of this document.

Limitation of Liability Polycom and/or its respective suppliers make no representations about the suitability of the information contained in this document for any purpose. Information is provided "as is" without warranty of any kind and is subject to change without notice. The entire risk arising out of its use remains with the recipient. In no event shall Polycom and/or its respective suppliers be liable for any direct, consequential, incidental, special, punitive or other damages whatsoever (including without limitation, damages for loss of business profits, business interruption, or loss of business information), even if Polycom has been advised of the possibility of such damages.

End User License Agreement By installing, copying, or otherwise using this product, you acknowledge that you have read, understand and agree to be bound by the terms and conditions of the End User License Agreement for this product. The EULA for this product is available on the Polycom Support page for the product.

Patent Information The accompanying product may be protected by one or more U.S. and foreign patents and/or pending patent applications held by Polycom, Inc.

Open Source Software Used in this Product This product may contain open source software. You may receive the open source software from Polycom up to three (3) years after the distribution date of the applicable product or software at a charge not greater than the cost to Polycom of shipping or distributing the software to you. To receive software information, as well as the open source software code used in this product, contact Polycom by email at OpenSourceVideo@polycom.com.

Customer Feedback We are striving to improve our documentation quality and we appreciate your feedback. Email your opinions and comments to DocumentationFeedback@polycom.com.

Polycom Support Visit the [Polycom Support Center](#) for End User License Agreements, software downloads, product documents, product licenses, troubleshooting tips, service requests, and more.

Contents

RealPresence Capture Server Introduction	2
Before You Begin	2
Unpack the Package	3
Install RealPresence Capture Server	3
Set Media Storage	4
Configure the System	4
Obtain Product Activation Key from Polycom	5
Initial System Configuration	5
Set RealPresence Capture Server IP Address	5
Set up the Gatekeeper	7
User Interfaces	10
Start a Recording	10
Record from RMX via Recording Link	12
Play Back Media Archives	12
View Live Streams	12



About This Guide

This guide explains how to install and set up the Polycom RealPresence Capture Server, it will step you through how to record your first video call and how to play the media file in a compatible web browser. The topics in this guide include:

- [Set up RealPresence Capture Server](#)

Gives a general introduction of this product and describes the steps required to perform the initial installation and setup.

- [Record and View Meetings](#)

Details how to record your first video call, view live streaming and how to play back the archive media file in a compatible web browser.

Set up RealPresence Capture Server

The following sections give a general introduction of the RealPresence Capture Server and describe the steps required to perform the initial installation and setup.

- [RealPresence Capture Server Introduction](#)
- [Before You Begin](#)

RealPresence Capture Server Introduction

The Polycom® RealPresence Capture Server is a streaming and recording system that participates in standards-based video and telepresence calls that can be used alone or as an integrated component of Polycom Video Content Management solution. As a native part of the Polycom RealPresence Platform, the RealPresence Capture Server records, archives, and streams telepresence and video conferences for playback on a variety of client devices including tablets, smart phones, desktop computers, and standards-based video endpoints.

By leveraging RealPresence Capture Server with existing telepresence systems, video conferencing endpoints and video infrastructure, or familiar unified communications (UC) tools, your organization can easily convert real-time conferences and events into reusable multimedia assets. Following are some features of RealPresence Capture Server:

- It integrates with Polycom endpoints and conference platforms for automated recording and playback.
- It supports H.323 and Session Initiation Protocol (SIP) standards for interoperability with third-party conferencing systems.
- It can output a maximum stream (live or video on demand) of 1080p HD (people + content combined).
- It provides access to live and video call archive streams on devices with compatible browsers including PC, MAC, iOS, and Android devices.
- It enables you to access video call archives via any standard-based endpoint.
- It provides REST API support for third-party integrations.

Polycom now offers a virtual edition of the RealPresence Capture Server system, this edition is packaged as an Open Virtualization Archive (OVA) file. The OVA file contains the RealPresence Capture Server application and information about its virtual machine environment. It can be installed as a virtual instance on a host machine running VMware vSphere.

Before You Begin

Hardware Requirements

The following table shows the hardware requirements for the RealPresence Capture Server.

Hardware Requirements

Simultaneous Recording Ports	6	12	18	40
LIVE Stream	3	6	9	0
Virtual Cores	8+	12+	16+	8+
CPU	<ul style="list-style-type: none"> 2.67GHz (Intel® Xeon® CPU x5650 @ 2.67GHz or better) CPU 2.90GHz (Intel Xeon CPU E5-2690 @ 2.90GHz or better) CPU 	<ul style="list-style-type: none"> 2.67GHz (Intel® Xeon® CPU x5650 @ 2.67GHz or better) CPU 2.90GHz (Intel Xeon CPU E5-2690 @ 2.90GHz or better) CPU 	<ul style="list-style-type: none"> 2.67GHz (Intel® Xeon® CPU x5650 @ 2.67GHz or better) CPU 2.90GHz (Intel Xeon CPU E5-2690 @ 2.90GHz or better) CPU 	<ul style="list-style-type: none"> 2.67GHz (Intel® Xeon® CPU x5650 @ 2.67GHz or better) CPU 2.90GHz (Intel Xeon CPU E5-2690 @ 2.90GHz or better) CPU
Minimum RAM	16 GB	16 GB	32 GB	32GB
Minimum Accessible Storage	80 GB	120 GB	120 GB	120 GB
Software Requirements	VMWare vSphere 5.1/5.5	VMWare vSphere 5.1/5.5	VMWare vSphere 5.1/5.5	VMWare vSphere 5.1/5.5



Please ensure sufficient CPU and memory resources are reserved for VMware as required on the table, otherwise the System may not function properly or in the worst case may fail to respond.

Software Requirements

RealPresence Capture Server - Virtual Edition is supported on VMware vSphere 5.1/5.5. Before you install and configure the RealPresence Capture Server system, you need the following:

- VMware vSphere 5.1/5.5 client installed where you can access the ESXi host
- Login credentials and IP addresses of one or more VMware vSphere hosts on which you will deploy your RealPresence Capture Server OVA
- A web browser where you access the Viewer Portal. See [table "Web Browser Requirements"](#) for the supported versions

For VMware vSphere ESXi and client v5.1 or 5.5 installation guide, refer to [VMware website](#).

Resource and License Management

For the 1st installation of Virtual Edition, the 90-day trial license provides 6/3 capacity and basic functions. To permanently enable the Capture Server system and enjoy the full capabilities, a RealPresence Capture Server license is required. For this release, the 6/3 model is supported for Virtual Edition only, which is different from the Appliance Edition.

Licence of Capability

License
6 Calls Record
3 Calls (of the 6 total calls) stream live

Web Browser Requirements

The following table shows the web browser requirements for RealPresence Capture Server.

User Portal Web Browser Requirement

Operating System	Browser Name	Version
PC (Windows 7, and Windows 8)	Internet Explorer	9, 10, 11
	Firefox	32, 33
	Chrome	38, 39
MAC OS-X (Intel-based Leopard, Snow, and Lion)	Safari	7.1, 8.0
	Firefox	32, 33
	Chrome	38, 39
iOS 7, 8	Safari	7.1.2, 8.1.1
Andriod phone and tablet	Android browser	4.3, 4.4.2

Set up RealPresence Capture Server in a Virtual Environment

The following steps assume you are familiar with deploying applications into a VMware environment. For more information about deploying applications into a VMware environment, see [VMware website](#).

To set up RealPresence Capture Server in a virtual environment:

- 1 Obtain the RealPresence Capture Server OVA package.
- 2 Deploy the OVA file into the VMware vSphere hosts that you have set up.



If the VMware vSphere host is very busy or it does not meet the RealPresence Capture Server hardware requirements, the deployment may fail. See [table "Hardware Requirements"](#) for details.

- 3 From the vSphere client, edit the instance and configure to the customer options.
- 4 Click the **Summary** tab and note down the IP address of RealPresence Capture Server system assigned by DHCP.
- 5 On VMware console, click **Edit** and adjust the CPU, memory, and the minimum disk space.

Configure NFS (Required)

Capture server virtual edition requires a NFS share as its media storage. The procedure below demonstrates how a NFS share is configured on a typical Linux distribution.

Make sure that NFS is co-located on the same switch/location as the Capture Server system to ensure stable I/O operations.

To export a shared storage location via NFS on a typical Linux system, CentOS used in below example:

- 1 Make sure the NFS service has been installed and is running.

Examples:

```
[root@centos-nfs ~]# service nfs status
rpc.svcgssd is stopped
rpc.mountd (pid 20129) is running...
nfsd (pid 20194 20193 20192 20191 20190 20189 20188 20187) is running...
rpc.rquotad (pid 20125) is running...
```

- 2 Edit NFS configuration file /etc/exports to set the file system paths for export.

Examples:

```
[root@centos-nfs ~]# cat /etc/exports
/home/nfs *(rw,no_root_squash)
/home/nfs_zip_1 192.168.9.78(rw,no_root_squash)
```

3 Restart the NFS service.**Examples:**

```
[root@centos-nfs ~]# service nfs restart
Shutting down NFS daemon: [ OK ]
Shutting down NFS mountd: [ OK ]
Shutting down NFS quotas: [ OK ]
Shutting down NFS services: [ OK ]
Starting NFS services: [ OK ]
Starting NFS quotas: [ OK ]
Starting NFS mountd: [ OK ]
Stopping RPC idmapd: [ OK ]
Starting RPC idmapd: [ OK ]
Starting NFS daemon: [ OK ]
```

4 Go to **Configuration > Media Storage Settings and configure the settings.****To save your media files on a network file system:**

- 1 Click **Configuration > Media Storage Settings**.**
- 2 Configure the following settings for the network file system.**

Media Storage Setting

Parameter	Description
NFS Server Name	Enter a name for the NFS server.
NFS Server Address	Enter an address of the NFS server.
NFS Storage Folder	Specify the folder path to the NFS storage. Note: Make sure the NFS server is set up beforehand.
Test	Test whether the NFS server is reachable.
Synchronize archives when storage setting changed	When this option is checked, the archives on the storage will be synced up with the archive record in the system database, and could be viewed from portal (viewer or admin). The sync-up action takes effect after the system restarts.
Send warning e-mail to Admin when remaining NFS free space reaches: (GB)	Set a NFS storage space threshold. You can set a value in the range of 10-50GB. After the system reaches the threshold, RealPresence Capture Server will send notifications to specified receivers.

3 Click **OK. The server restarts to apply your changes.**

- If Network storage is disabled or error, RealPresence Capture Server cannot dial in and dial out.
- Capture Server supports NFS Version 2 and 3.

Initial System Configuration

To configure the system for use, you need a compatible web browser to access and use the Administration user interface (Hereafter referred to as Admin Portal) to achieve this. The initial configuration consists of three steps:

- Obtain the Product Activation Key from Polycom
- Set the RealPresence Capture Server IP address
- Set up the Gatekeeper

Obtain Product Activation Key from Polycom

A new installation of RealPresence Capture Server Virtual Edition comes with a 90-day trial license.

To obtain the product activation key:

- 1 Go to **Admin > Product Activation** to obtain the serial number. Write it down for later use.
- 2 Enter the following web site address in the address bar of the web browser: support.polycom.com. and go to **Support Home**.
- 3 Go to **Licensing & Product Registration > Activation/Upgrade**.
- 4 Click **All other Polycom Products** in the pop-up window.
- 5 Enter your e-mail address and password to log in to or register for a new account.
- 6 Follow the page prompts step by step to generate the Key Code required for system activation.
- 7 Enter the **Serial Number** you recorded and click **Next**.
- 8 Follow the page prompts step by step to generate the Key Code required for system activation.
- 9 Note down the activation key (Key Code) on the page and click **Upgrade**.
- 10 Go back to Capture Server Admin Portal and activate the system under **Admin > Product Activation**.

Configure IP Settings through Console

By default, when a new RealPresence Capture Server is started, it obtains an IP address from the DHCP server automatically. Follow the steps below to check the IP address assigned by DHCP server. You can configure IP settings from either Capture Server system's Console or Admin Portal.

To view the system IP address in the RealPresence Capture Server's console:

- 1 Open the console of your RealPresence Capture Server.
- 2 The default console display is shown in the next illustration

- 3 The IP address displayed on console is shown in the above illustration, the default IP address is



```

Polycom RealPresence Capture Server
Copyright 2010-2013 Polycom, Inc. All Rights Reserved.
Device Network Information:
eth0{192.168.1.254}          eth1{ }
Use a supported browser to configure/manage this Polycom RealPresence Capture Server:
http://192.168.1.254
Use a supported telnet client to configure/manage this Polycom RealPresence Capture Server:
192.168.1.254

```

<https://192.168.1.254>

- 4 If needed, modify the RealPresence Capture Server IP address in the Admin UI. See [Configure IP Settings through Admin Portal](#)
- 5 Type **Alt+F2** keys to go to the login screen.
- 6 Enter the user name and password (both are **polycom** by default).
- 7 Set RealPresence Capture Server a static IP or DHCP for LAN interface using `Network Settings` command, refer to [Network Settings](#) for details.
Note: After you are finished with DHCP setting configuration, go to console and get the IP address information assigned by DHCP server.
- 8 After you set the IP, the Capture Server system will ask if you want the changes, click **Yes** to reboot.

To download Capture Server software and VE version:

- 1 Go to **Admin > Product Activation** to obtain the serial number. Write it down for later use.
- 2 Enter the following web site address in the address bar of the web browser: support.polycom.com. and go to **Support Home**.
- 3 Go to **DOCUMENTS & DOWNLOADS > UI Infrastructure**.
- 4 Click **Video Content & Management Solutions** at the left side bar.
- 5 Click **Polycom RealPresence Capture Server, Virtual Edition**.
- 6 Enter your e-mail address and password to log in to or register for a new account.
- 7 Click the EULA and agree to it.
- 8 Click **Submit**.
- 9 Go to Capture Server Admin Portal and activate the system under **Admin > Product Activation**.

To view the system activation status:

- » Go to **Admin > Product Activation**. Below system information are displayed:

Parameter	Description
License Type	Permanent license.
Software Version	Current version of the software running on the system.
Serial Number	The product serial number
Activation Status	Whether the system is activated, after the system is successfully activated, Active displays.
Max Recording Ports	Maximum number of recording ports supported by the system.
Max Live Streaming Ports	Maximum number of live streaming ports supported by the system.
Max Streaming Sessions	Maximum number of video-on-demand and live streaming sessions supported by the system. Base: 250. Note: After purchasing and activating the license, the streaming sessions capacity will be increased from 250 to 500.
Media Encryption	Whether the AES encryption function of the system is activated. This is a charged function. You can use it only after purchasing and activating the license.
Streaming without recording (no archive)	Whether the streaming without recording function of the system is activated. This function is activated by default, the system performs live streaming without recording and no archives are generated.
Timecode Watermark	Whether the basic timecode watermark capability for transcoded mp4 on-demand files is activated. On-demand archives can be output with basic timecode watermarking.

Configure IP Settings through Admin Portal

The RealPresence Capture Server system supports both IPv4 or IPv4 & IPv6 network communications. You can configure parameters to be used for network communication, including system IP address, DNS server, NAT server.



The RealPresence Capture Server system supports IPv6 system management.

To set IP:

- 1 Go to **Configuration > IP Settings** and configure the following settings:

Set IP Parameters

Parameter	Description
Enable Network Separation	Select this check box to route the management, streaming traffic and video call traffic through LAN 1 and LAN 2 interfaces separately. This offers higher security for the signaling data.
Obtain an IP Address Automatically (DHCP)	If you select this radio button, RealPresence Capture Server obtains an IPv4 address automatically via DHCP. Note: Obtaining an IP address automatically is not recommended. For best results, assign a static IP to RealPresence Capture Server.
Using the following IP Address	<ul style="list-style-type: none"> • IP Address: the IP address of the system. • Subnet Mask: the subnet mask of the system. • Default IPv4 Gateway: the address of the interface to use for accessing the IPv4 gateway. • Preferred DNS Server: the preferred DNS server address for the system to resolve domain names. • Alternate DNS Server: the alternate DNS server address for the system to resolve domain names.
Enable IPv6	Specify whether to enable IPv6 related functions.
Obtain an IP Address Automatically (IPv6)	Specify whether to obtain the IPv6 address automatically using Stateless Address Auto-configuration (SLAAC). Note: Obtaining an IP address automatically is not recommended. For best results, the system should be configured with a static IP address.
Using the following IP Address (IPv6)	Select this option to manually configure a static IPv6 address: <ul style="list-style-type: none"> • Link Local Address: Specify an address for link local communication. Routers do not forward packets with link local addresses. • Site Local Address: Specify an address for site local communication. Routers do not forward packets with site local addresses. • Global Address: Specify one or several address for communication with external IPv6 networks. Separate several addresses with a comma (,). • Default IPv6 Gateway: Specify the address of the interface to use for accessing the IPv6 gateway.
Enable ICMP V6 DAD	Specify whether to enable Duplicate Address Detection (DAD) to ensure the IPv6 address set to the system is unique in the local network.
Enable ICMP Echo	Specify whether to allow the system to respond to an ICMP (Internet Control Message Protocol) echo request (Ping) sent from other devices in the network. In some high-security environments, you may need to disable this option to protect the system from Ping attacks.
MTU	Specify the Maximum Transmission Unit (MTU) size.

LAN Speed	Specify the speed or duplex modes for the LAN port. Select Auto to let the system set the speed automatically. Note: When setting the LAN port speed, contact your network administrator to ensure that the switch link rate matches the system port speed.
NAT Public (WAN) Address	Set the external IP address in Network Address Translation (NAT) environment. NAT environments use private internal IP addresses for devices within the network, while using one external IP address to allow devices outside the LAN to access Capture Server Web Portal, view live streaming or VoD playback.

2 Configure the following general settings:

General System Network Parameters

Parameter	Description
Host Name	Specify the host name of the system.
Domain	Specify the domain name of the system.

3 Click **Add** to add static routes. You need to enter the following information for each route:

Set Route Parameters

Parameter	Description
Destination	Specify the IP address of the destination network.
Gateway	Specify the IP address of the gateway to access the destination network.
Subnet Mask	Specify the subnet mask for the destination network.

4 Click **OK**. The system restarts to apply your changes.

Set up the Gatekeeper

If a gatekeeper is configured on your network, you can register RealPresence Capture Server to the gatekeeper to simplify calling.

To register the system to a gatekeeper to make H.323 calls:

- 1 In the web browser's address line, enter the system's IP address in this format: **https://<system IP address>/admin**.
- 2 Go to **Configuration > Signaling Settings > H.323**.
- 3 Select **Register To Gatekeeper**.
- 4 Configure the following settings. After you finish the configuration, click **OK**.

Parameter	Description
Gatekeeper type	Choose between Polycom and Cisco VCS .
Primary Gatekeeper	Indicates whether the system is registered to the primary gatekeeper.

Gatekeeper Address	Specify the IP address for the gatekeeper. Note: Never enter Capture Server's IP address.
Gatekeeper Port	Specify the port number for the gatekeeper, the default value is 1719.
Register User Information for Gatekeeper	Specify whether to register the system to a Polycom Gatekeeper server for H.235.0 authentication. When H.235.0 authentication is enabled, the gatekeeper ensures that only trusted endpoints are allowed to access the gatekeeper.
Gatekeeper User	Specify the user name for registration with the Polycom Gatekeeper server.
Gatekeeper Password	Specify the password for registration with the Polycom Gatekeeper server.
Alternate Gatekeeper	Indicates whether the system is registered to the alternate gatekeeper. Note: The alternate gatekeeper is used only when the primary gatekeeper is not available.
System Prefix / E.164	Specify the E.164 number for the system.
System H.323 Alias	Specify the H.323 alias for the system.
Remote Display Name	Specify the name to be displayed to the far end. Note: If you set the remote display name with dual-bytes characters like Chinese, you will not see the characters on the far end endpoints in a H.323 call between endpoints and the Capture Server system.

Record and View Meetings

The following topics demonstrate how to record your first video call, view the live streaming, play VoD and live streaming, and how to play back media archives in a compatible web browser.

- [User Interfaces](#)
- [Start a Recording](#)
- [Play Back Media Archives](#)
- [View Live Streams](#)

User Interfaces

RealPresence Capture Server provides four interfaces that are used for specific purposes:

- **Web-based Admin Portal:** Accessed via a compatible web browser, the Admin Portal is used to configure the system, set up recording parameters, monitor system use and health, dial out to endpoints to record meetings, disconnect calls in progress, create different transcoded versions of archived calls, download media files, and give admin users a quick way to access and play archives and live streams.
- **Web-based Viewer Portal:** Accessed via compatible device/web browser (PC/MAC, iOS and Android), the Viewer Portal UI is used to find, navigate, search, play archives and live streams.
- **TV user interface (also called the “TVUI”):** Accessed via standards-based video conferencing endpoints, this interface can be used to record meetings.
- **Console:** Accessed via vSphere client console or SSH, console is used to view/change IP settings and reboot the system.

For more information, see the User Guide.

Start a Recording

You can start recording in RealPresence Capture Server using one of the following methods:

- Call from RealPresence Capture Server to an interoperable endpoint from Admin Portal.
- Call from RealPresence Capture Server to an interoperable endpoint from User Portal.
- Call RealPresence Capture Server from an interoperable endpoint.
- Start a recording from Polycom RMX system via recording link.
- Schedule a meeting on RealPresence Media Manager and connect the RealPresence Capture Server to an endpoint.

To start a recording from the Admin Portal:

- 1 Access Capture Server admin portal by its IP address or host domain name from a compatible browser.
- 2 Enter the user name and password to log in to the system.
- 3 Go to **Home**. In the **Signaling Connection** area, click **Dial out to record**.
- 4 Configure the following settings:

Parameter	Description
Address	<p>Specify the calling address.</p> <p>The system supports entering the calling address with an extended service number in the address box.</p> <p>If you call a H.323 system, you can dial out to endpoints by entering the numbers in the following formats:</p> <ul style="list-style-type: none"> • [far end E.164 prefix] - Use when every system has registered to a gatekeeper. For example, if a far end system E.164 prefix is 9988. • [Far End H.323 ID]- Use when every system has registered to a gatekeeper. For example, if a far end system H.323 ID is CS9988. • [Far End IP Address]- Use when a system has not been registered to a gatekeeper. For example, if a far end system IP address is 172.22.33.44.
Signal	Set the H.323 or SIP network type for the system to place a call. Your choice depends on the call type used by the peer device.
VRR Name	Click Select to select a virtual recording room (VRR). You can use the built-in default VRR, or one you have created.
Event Name	Specify a unique name for this event.
Max Call Rate (Kbps)	Display the maximum call rate specified in VRR.

- 5 Click **OK**.



- **Dial out to record** is also available under **Call** menu from Admin Portal.
- The recording starts immediately if **Start Recording Immediately** is enabled in the selected recording template.
- Unlike administrators, normal users can only view and manage calls started by themselves.

Dial in from Endpoint

You can start recording by dialing RealPresence Capture Server or dial in to a VRR directly to start recording.

To start recording by dialing RealPresence Capture Server:

- » Enter the E.164 prefix or H.323 ID or SIP URL of RealPresence Capture Server on the user interface of an interoperable endpoint, for example, from remote control of HDX or Group Series.

If your system or endpoint is not registered to the gatekeeper or to a SIP server, call the system IP address instead.

You can also dial in to a VRR directly to start recording by dialing one of the following:

For H.323 calls

- [RealPresence Capture Server IP]##[VRR number]
For example, if the RealPresence Capture Server IP is 11.12.13.14, and the VRR number is 4096, dial *11.12.13.14##4096*.
- [RealPresence Capture Server E.164 prefix][VRR number]
For example, if the RealPresence Capture Server E.164 prefix number is 8888, and the VRR number is 4096, dial *88884096*.

For SIP calls

- [VRR number]@[RealPresence Capture Server IP]
For example, if the RealPresence Capture Server IP is 11.12.13.14, and the VRR number is 4096, dial *4096@11.12.13.14*.
- [SIP peer prefix][VRR number]
If the system has been registered to a SIP server, the SIP server should configure CaptureServer as a SIP peer. For example, if the SIP peer prefix of the Polycom RealPresence Capture Server system is 8888 and the VRR number is 4096, the dial string should be *88884096*.

Record from RMX via Recording Link


If you configure the Recording Link function on the Polycom RMX series conference platform and integrate the platform with the RealPresence Capture Server, the RealPresence Capture Server can be called automatically for recording when a multi-point conference is hosted through MCU.



For more information about configuring the Recording Link function on the RMX, refer to the User Guide provided with the RMX system.

Change Conference Layout for MCU hosted calls


Once the Recording Link function is enabled on RealPresence Collaboration Server system (version 8.4 or higher), If you dial into a conference which is hosted through MCU, the conference layout type can be changed once the call is connected. It's for SIP calls only. You can also set conference layout type in a recording template.

To set conference layout type in a recording template

- 1 Go to **Template > Recording Templates**.
- 2 Select a recording template you want to edit.
- 3 Click **Edit**.
- 4 Choose from the **Conference Layout** drop-down list:
 -  **Auto**: Automatic layout according to conference setting at RMX side to recording server

-  **1x1**: Single view to recording server.
-  **1x2**: Dual view to recording server.

To change conference layout type for an ongoing call

- 1 Go to **Signaling Connection** and click .
- 2 Choose from the following layouts:
 - **Auto**: Automatic layout according to conference setting at RMX side to recording server
 - **1x1**: Single view to recording server.
 - **1x2**: Dual view to recording server.



When an endpoint or MCU tries to connect by directly dialing the IP address or E.164 prefix of the RealPresence Capture Server system, the default VRR parameters are used to record. You can directly start recording using recording parameters defined in a VRR by adding the VRR number to the dial-in number. If the RealPresence Capture Server system is configured in connection with a Polycom RMX series system through the recording link, you can specify the VRR to be used by adding the VRR number in the **Recording Link** field on the Polycom RMX system. For more information, refer to the Polycom RMX system Administrator's Guide.

For prefix+VRR format, you need to add SIP Peer to Polycom DMA server, for details, refer to the Polycom DMA server's Administrator's Guide.



With the newly added Annex-O support, you can start recording by dialing one of the following:

- For incoming calls to Capture Server, the dial-in number is [VRR number]@[RealPresence Capture Server IP address].
- If you call from RealPresence Capture Server to an interoperable endpoint such as Polycom HDX Series system, the dial-out number is [RealPresence Capture Server E.164 suffix]@[HDX IP Address] or [RealPresence Capture Server H.323 ID]@[HDX IP Address]
- If you call from RealPresence Capture Server to a MCU, the dial-out number is [Conference ID]@[RMX IP Address]

Point-to-point Recording

Point-to-point recording allows a user to dial out to two endpoints from the Capture Server Admin Portal or User Portal, and record the two sites into same recording file.

To start point-to-point recording from Admin Portal

- 1 In the address line, enter the system's IP address in this format: <https://<system IP address>/admin>.
- 2 Enter the user name and password to log in to the system.
- 3 Go to **Home or Call**. In the **Signaling Connection** area, click **2 Sites Recording**.
- 4 Enter the addresses of the two H.323 endpoint participants.

5 Click **OK**.



- For now it is only available in H.323 point-to-point calls.
- For point-to-point recording from User Portal, refer to [To start point-to-point recording from User Portal](#)

Play Back Media Archives

You can play back recorded media archives stored in RealPresence Capture Server using one of the following methods:

- Play back from RealPresence Capture Server system's User Portal.
- Play back from the RealPresence Capture Server system's Admin Portal.
- Download recorded files and play back using compatible media players.


For more information, see the User Guide.



To view archives and live streams, your device must turn off the pop-up blocker. For example:

- For iPad: From **Settings > Safari**, make sure the option **Block Pop-ups** is **OFF**.
- For Android devices: From **Browser > Settings > Advanced**, make sure the option **Block Pop-ups** is **OFF**.
- For PC Internet Explorer (version 9.0 or above): From **Tools > Internet Options > Privacy**, make sure the option **Turn on Pop-up Blocker** is NOT selected.

To play back archives through the User Portal:

- 1 Log in to the User Portal.
- 2 Go to **Archives**.
- 3 Select the archive you want to play back and click .
- 4 A new window opens to play the video.

View Live Streams

You can view live streams from both RealPresence Capture Server User Portal and Admin Portal:

- View live streams from the RealPresence Capture Server system's User Portal.
- View live streams from the portal of external media servers, if configured.

To view your live streaming from the User Portal:

- 1 On a device with compatible web browser, open a supported web browser.
- 2 In the browser address line, enter the system's portal address, for example, **https://System IP**.
- 3 Click **Live Streaming** from the menu on the left.
- 4 Click the **Play** button of the live streaming that you want to play.

For more information of viewing live streams from Admin Portal, see the User Guide.